

مواصفات عامة للمودمات الخاصة بخدمة الـ (ADSL)

Modem Type : Wireless Ethernet Router

Qty : 10000

<b>General descriptions</b>	One Ethernet port USB (Optional) Wireless g – two antennas
<b>WAN protocols</b>	Bridged, ethoA,PPPoA,PPPoE
<b>LAN</b>	10/100Base-T (RJ45) MDI/MDI-x autosensing..
<b>WAN Port</b>	ADSL <b>RJ-11</b> , T1.413, G.DMT, G.Lite, ADSL2+, ITU Annex A.
<b>Modem Specifications</b>	ADSL ,ADSL2 ,ADSL2+ (auomode)
<b>Management</b>	Web management
<b>ATM</b>	Extensive multi-PVC ATM Quality of Service (UBR, CBR, VBR-rt, VBR-nrt)
<b>ADSL Filter</b>	Included
<b>SoftWare</b>	Latest Version
<b>Accessories</b>	one RJ11 cable , one RJ45 UTP cable , Setup CD, Guides
<b>IP Routing</b>	<ul style="list-style-type: none"><li>• UPnP certified Internet Gateway Device, enabling major conferencing and gaming technologies .</li><li>• IPSec passthrough from multiple LAN clients, enabling secure homeworking .</li><li>• Supports PPPoE, PPPoA, IPoA, CIP, ETHoA.</li><li>• DNS server and relay, DHCP server and relay.</li><li>• Network Address Translation for connection sharing, including support for SIP, H.323, Realaudio, FTP, IRC, IKE, IPSec-ESP, Jabber, ILS, ...</li><li>• Simultaneous bridging and routing of PPPoE connections, enabling network based VPNs .</li><li>• Port Forwarding - Single or Range of Ports.</li></ul>
<b>Features</b>	<ul style="list-style-type: none"><li>• <b>IPv6 Enabled</b></li><li>• Firewall: Stateful Packet Inspection, Intrusion logging and Reporting, Denial of Service protection</li><li>• VPN Functionality: NAT traversal (VPN pass-through) for IPSec, PPTP and L2TP VPNs.</li><li>• Mode of Operation: Network Address Translation (NAT), static routing</li><li>• IP Address Assignment: Static IP address assignment, internal DHCP server on LAN, DHCP client on WAN</li><li>• Input power : (.110V -240 V)</li></ul>

متطلبات اعدادات المودم :

- طباعة شعار يمن نت ملون على المودمات.
- عمل الإعدادات المطلوبة العاملة في يمن نت كإعدادات افتراضيه لجميع المودمات على النحو التالي:  
Default Protocol : PPPoE - LLC  
Vpi/Vci : 8/35  
مع امكانية تغيير الإعدادات بحسب الحاجة.
- توفير برشور باللغة العربية يشرح الاتي :
  - كيفية عمل الإعدادات الاساسية الخاصة باسم المشترك وكلمة المرور
  - كيفية تغيير كلمة السر الخاصة administrator للدخول لل Web Management
  - كيفية تغيير SIID والتشفير لاشارة اللاسلكي